

THE ARGEN CORPORATION**Product Specification Sheet****NOBLEBOND****Color:** WHITE**Type:** 4**ADA Classification:****NOBLE (N)****PGM:** 25 %**Metal Content %**

Ru	Co	Cr	Ga	B
25	40	24	11	x

'x' denotes a content of less than one percent.

Thermal Properties

Melting Range	Casting Temperature	Coefficient of Linear Thermal Expansion	
		(um/m-°C)	
2230-2590 °F	2770 °F	25-500	25-600
1220-1420 °C	1520 °C	13.8	14.3

Mechanical Properties

Vickers Hardness			Yield Strength		Modulus of Elasticity	Elongation	Density
(VHN)			(0.2% Offset)		(GPa)	(%)	(g/cm³)
A.F.	Soft	Hard	A.F.	Hard		A.F.	Hard
500	---	---	79,750 psi 550 MPa	--- psi --- MPa	250	3	---

PROCESS**INSTRUCTIONS FOR USE****Modeling**

Maintain a minimum wax thickness of 0.3 to 0.4 mm. The wax pattern design should have lingual collars and no sharp corners. Lingual eyelet rings help support castings during firing.

Spruing (Single Crowns)

Use direct sprues, 8-10 gauge, (3.3-2.6 mm diameter) and 1/2 in. (12 mm) long with adequate reservoirs. There should be no more than 1/4 in. (6 mm) of investment from the top of the pattern to the top of the investment.

Spruing (Multi-Units & Bridges)

Use a 6 gauge (4.1 mm diameter) runner bar, connecting the units to the bar with 10 gauge (2.6 mm diameter) sprues 1/8 in. (3 mm) long and joining the bar to the sprue base with 8 gauge (3.3 mm diameter) and 1/2 in. (12 mm) long sprues coming from a domed central entry point. There should be no more than 1/4 in. (6 mm) of investment from the top of the pattern to the top of the investment.

Alloy Quantity

9 g/cm³ * (Wax Weight) = Required Alloy Quantity.

Investing

Use debubbler and blow off any excess before investing.
Recommended Investment: Phosphate Bonded (Carbon Free).
Follow the manufacturer's instructions.

Burnout

After adequate set-up time, place the ring(s) in a room temperature oven and raise the temperature to 870 °C / 1600 °F for 1 hour plus 10 minutes for each additional ring. If you are using a rapid fire investment, follow the manufacturer's instructions.

Reusing Cast Alloy

Use only clean buttons and at least 35 percent new alloy.

Crucible Type

Ceramic

Torch Casting

Use either a natural gas/oxygen or a propane/oxygen torch with a multi-orifice tip. Ensure that the flame is on a Neutral setting when casting. The fuel proportions should be one-part fuel to two-parts oxygen

Induction or Electrical Casting

Use a ceramic crucible and a casting temperature of a least 150°C / 300°F over liquidus temperature. Every casting machine is different. The casting temperature may require adjustment based upon the alloy and the amount of metal being cast.

Cooling

Allow casting ring to cool to room temperature. DO NOT quench in water.

Divesting and Cleaning

Divest and sandblast with 50 micron aluminum oxide, be careful of margins.

Finishing

Grind the metal surfaces for porcelain application with non-contaminating aluminum oxide stones in one direction. Blast with non-recycled 50 micron aluminum oxide. Do not exceed a blast pressure of 4 bars or 60 psi. Clean in distilled water in an ultrasonic cleaner for 10 minutes.

Oxydizing or Degassing

650-1010°C,
1200-1850°F,

Vacuum, no hold, remove oxide

Solder joints should be as large as possible (at least 5 mm²). Soldering gap approximately 0.05-0.2 mm. The solder joints should be parallel and free of debris. Preheat invested units and pressure blast with 50 micron just before soldering to remove oxide. If flux is used, it should be water soluble..

Use: Co/Cr Pre

Presolder

NOTE:

Our first recommendation is laser welding with LWNPCO.

NobleBond can be pre-soldered with Co/Cr pre-solder following normal procedures for pre-soldering non-precious alloys.

Porcelain Application

Follow the recommendations of the porcelain manufacturer. For a better bond, fire a thin wash 10 - 15 °F (10 °C) above normal temperature, followed by regular opaque coats.

We recommend drying paste opaque from the inside out; this is done by utilizing a hot plate. The units are placed on a honeycomb sagger tray with metal pins. This is placed on top of the burner set a low to medium setting (approx. 250°F).it will take approximately 8-10

minutes or until the opaque turns chalky white or flat color. Then place in furnace for entry and maturing.

Solder joints should be as large as possible (at least 5 mm²). Soldering gap approximately 0.05 - 0.2 mm. Cover ceramically-veneered units with wax before investing. The soldering investment should not come in contact with the ceramic. The soldering surfaces should be parallel, smooth and free of debris.

Post Soldering After Firing

Use: NOT RECOMMENDED

Laser Wire

LWNPCO

Polishing

For ceramic alloys use diamond paste and/or Tripoli and rouge with soft bristles and chamois wheels. High shine with clean soft bristle brushes and/or muslin wheel.

Print Date 6/13/2018